

## USER'S MANUAL

### 1Eyes 200W LED COB Cool Warm White Lighting



#### Maintenance

1. Please keep the light in dryness and avoiding use in wet place.
2. Using intermittently can be extended the life.
3. Attention to clean the fan and lens usually in order to get the ventilating effects and lighting effects better.
4. Please do not wipe the crust using organic menstruum for avoid to damaged the product.

#### Statement

The product has well capability and intact packing when leave factory, All of the user should comply with above warning item and manual, any misuse cause of the damages are not included in our guarantee, and also can't be responsible for any malfunction & problem owing to ignore the manual. Please forgive that we will not be notice for technical change

#### Attention Item

1. For guarantee the life of product, please do not put it on the wet place and not use it the place over 40 degree.
2. Please don't lay the product on the un-fixable or shakable place.
3. Ask for the professional to maintain the product in order to avoid the danger of get an electric shock.

4. Power supply should not be changed over  $\pm 10\%$  while the light is using, it will be decreased the life of lamp if the power is too high, but it will be influenced the luminosity if the power is too low.
5. After power off, if it is need used again, please cool down over 20 minutes.
6. Please look round the manual for ensure the product can be used normally.

### DMX Channel Summary-6 Channels Mode(H)

Channel	Value	Function
CH1	0-255	Total dimming
CH2	0-255	Strobe
CH3	0-50	no effect
	51-100	Color selection mode
	101-150	Jump mode
	151-200	Gradient mode
	201-250	Self-propelled mode
	251-255	Voice control mode
CH4	0-255	CH3 speed adjustment
CH5	0-255	Cold white
CH6	0-255	Warm White

### DMX Channel Summary-4 Channels Mode(R)

Channel	Value	Function
CH1	0-255	Total dimming
CH2	0-255	Strobe
CH3	0-255	Cold white
CH4	0-255	Warm White

### DMX Channel Summary-2 Channels Mode(d)

Channel	Value	Function
CH1	0-255	Cold white
CH2	0-255	Warm White


### Display Control Instruction

Display	Value	Function
H001	001- 512	6 channel mode
A001	001- 512	4-channel mode
d001	001- 512	2-channel mode
CL00	0-3	Selection of color
CC01	0-15	Color jumps

dE01	0-15	Color gradient
cp01	0-15	The program is self-propelled
U255	0-255	Cold white
C255	0-255	Warm White
F255	0-255	Strobe
suod	suod	Voice control mode

## Display Control Instruction

Welcome to use our light. The light uses energy-saving LED, long Product life, shockproof, dustproof, DMX receiver and self-running feature, which can produce a variety of vivid lighting effects, easy to operate, suitable for all types of entertainment decoration, architectural lighting industry.



Instructions: Press the function key A cycled out the eight different function effects, digital tube first two digits on behalf of which the current function (see menu). The last two digits represent the functions in which the address code or speed parameters. Press the B or C key to modify the parameter values. Press the D key to confirm.

---

## Product Introduction

- \* Power Supply:AC90--275V,50--60HZ
- \* Power consumption:200W
- \* Fixing lamp:LED 200W Cool Warm White
- \* DMX-Control-channels:6/4/2 DMX Channels
- \* Shuttle:Flash rate:0--10HZ
- \* Dimmer:0-100% mechanic dimmer
- \* Long Lifespan LEDs(more than 60,000 hours)