

## USER'S MANUAL

### LED Flat Par 12x3W Violet Color Lighting



#### Maintenance

1. Please keep the light in dryness and avoiding use in wet place.
2. Using intermittently can be extended the life.
3. Attention to clean the fan and lens usually in order to get the ventilating effects and lighting effects better.
4. Please do not wipe the crust using organic menstruum for avoid to damaged the product.

#### Statement

The product has well capability and intact packing when leave factory, All of the user should comply with above warning item and manual, any misuse cause of the damages are not included in our guarantee, and also can't be responsible for any malfunction & problem owing to ignore the manual. Please forgive that we will not be notice for technical change

#### Attention Item

1. For guarantee the life of product, please do not put it on the wet place and not use it the place over 40 degree.
2. Please don't lay the product on the un-fixable or shakable place.
3. Ask for the professional to maintain the product in order to avoid the danger of get an electric shock.

4. Power supply should not be changed over +&-10% while the light is using, it will be decreased the life of lamp if the power is too high, but it will be influenced the luminosity if the power is too low.
5. After power off, if it is need used again, please cool down over 20 minutes.
6. Please look round the manual for ensure the product can be used normally.

## DMX Channel Summary-8 Channels Mode

Channel	Value	Function
CH1	Total Dimming	Total dimming
CH2	0--255	Purple 1 dimming
CH3	0--255	Purple 2 dimming
CH4	0--255	Purple 3 dimming
CH5	0--255	Purple 4 dimming
CH6	Total Strobe	Strobe from fast to slow
CH7	0-250	Auto
	251-255	Sound
CH8	CH7 control speed	Control speed for CH7, Auto+Sound Mode

## Display Control Instruction

No	Display	Function
1	<i>A001</i>	0-512, DMX Mode
2	<i>Adye</i>	Adye/Adno, NO
3	<i>Au01</i>	01--08, light mode(8 kinds)
4	<i>FF90</i>	0-99, between the colorful gradient and colorful jump
5	<i>EE90</i>	0-99, colorful gradient
6	<i>CC90</i>	0-99, colorful jump
7	<i>FO00</i>	0-255, colorful gradient

8	Strobe	Flash, from slow to fast
9	Sound	Sound Mode
No	Display	Function

## Display Control Instruction

Welcome to use our light. The light uses energy-saving LED, long Product life, shockproof, dustproof, DMX receiver and self-running feature, which can produce a variety of vivid lighting effects, easy to operate, suitable for all types of entertainment decoration, architectural lighting industry.

E

A:Function

B:Up

C:Down

D:Enter

E:LED Display



A

B

C

D

Instructions: Press the function key A cycled out the eight different function effects, digital tube first two digits on behalf of which the current function (see menu). The last two digits represent the functions in which the address code or speed parameters. Press the B or C key to modify the parameter values. Press the D key to confirm.

---

## Product Introduction

- \* Power Supply:AC90--275V,50--60HZ
- \* Power consumption:36W
- \* Fixing lamp:LED 12×3W Violet Color
- \* DMX-Control-channels:8 DMX Channels
- \* Shuttle:Flash rate:0--10HZ
- \* Dimmer:0-100% mechanic dimmer
- \* Long Lifespan LEDs(more than 60,000 hours)

# SHEHDS